

CSCI 2330 – x86-64 Assembly Exercises #1

1. For each of the following x86-64 instructions, rewrite as a C-style command using assignment (=), pointer dereferencing (*), and regular arithmetic operators (+, -, etc). You can use register names as subexpressions – e.g., "**movq %rax, %rcx**" could be rewritten as "**rcx = rax**". Assume no data size scaling for C pointer arithmetic.

- (a) **addq %rax, %rcx**
- (b) **movq %rax, (%rcx)**
- (c) **subq (%rax), %rcx**
- (d) **leaq (%rax), %rcx**
- (e) **leaq 9(%rax, %rdx), %rbx**
- (f) **addq 9(%rax, %rdx), %rbx**

2. Assuming **func1** and **func2** are non-void functions that each take two arguments, rewrite the following x86-64 instructions as a series of C-style function calls. You can define and use any variables you wish.

```
movq    $5, %rsi
movq    $8, %rdi
callq   func1
movq    %rax, %rsi
callq   func2
movq    %rax, %rdi
callq   func1
```

3. Rewrite the x86-64 instructions below as a C function, which you can assume returns an **int** and takes two **int** arguments. You can use any variable names you wish.

check:

```
subl    $4, %edi
cmpl    %edi, %esi
setl    %al
movzbl  %al, %eax
ret
```